

Error 3070 when reading Black Trap

This error is a Unispef error meaning black trap diagnostic failed.

To determine whether is hardware or software problem try running: `Terminal` program located in `ColorTools` folder.

Choose `File`, `Open`, click on `MC90.TRM`

Pick : `Settings`, `Communications`. Verify settings are: 19200 baud, 1 stop bit, no parity, none flow control.

On buttons, click on: `*` then on `Capabilities`. (write down the string)

Click on `*`: then on `Measure`.

Does it have a valid measurement? Or any measurement?

You can measure black trap here with `measure` button and see

if it is normal, and also check white tile. If its zeroes, it's a hardware problem.

Author: Datacolor

Saved From: <http://knowledgebase.datacolor.com/article-27.html>